

Service Information

1997-08-25

HQ 482/A/B HQ 484/A/B
HQ 486/A/B

DAP 152

Domestic Appliances and Personal Care

With the introduction of the /B version the PCB 4822 214 70594 (/A version, item 4) will be no longer available. Reference will be made to **4822 214 12213**.

When fitting a new PCB proceed as follows:

The old battery (4/5AA size) has to be fitted in the opposite direction, where an assembly wire has to be used to interconnect the '-' soldertag and PCB.

When fitting a new battery of the AA size too, see to it that in the cover (item 16) near the screw hole 2 pegs are removed.

Old stock of covers 4822 441 11528, 4822 441 11534 and 4822 441 11535 may show above-mentioned pegs. When used for the /B versions, the pegs must be removed.